

AstroFXAudio Digital 5.1/7.1 Audio Systems	AstroFXAudio SP Advanced	AstroFXAudio Standard	AstroFXAudio Advanced
Certified for domes up to 30' (9.1m) or in less critical applications.	Yes	No	No
Certified for domes of any size where the ultimate in audio is required.	No	Yes	Yes
5.1 Sound System with five high-efficiency speaker systems for L-R-C-Ls-Rs and a subwoofer system with <i>tunable active crossovers</i> at 80Hz	Yes	Yes	Yes
Includes digital inputs from astronomy projection system and Operator's Console mixer (if available).	No	Yes	Yes
Professional grade standard amplifiers.	Yes	No	No
Digital THX™ cinema amplifiers.	No	Yes	Yes
Premium digital THX™ cinema amplifiers.	No	No	Yes!
Professional CD audio deck with 232 port.	Yes	Yes	Yes
Professional standard 1440 frequency UHF wireless with lavalier, handheld and headset mics.	Yes	Yes	No
Premium advanced professional 1440 frequency UHF wireless with lavalier, handheld and headset mics.	No	No	Yes
Console mic jack plate and folding tripod mic stand.	Yes	Yes	Yes
A backup hardwired handheld mic, cabling, and stage mic jack plate with two mic jacks.	Optional	Optional	Yes
iPod or Auxiliary stereo audio input at console rack.	No	Yes	Yes
Rackmount stereo console mixer.	10-input	16-input	16-input
AstroFXAudio computer programmable digital audio processor,	Basic Version	Premium Version	Premium Version
Three fader/four button remote control panel. Can be upgraded with AstroFXCommander system.	Yes	Yes	Yes
Professional 1/4', 48-point professional, hardwired, balanced audio patch bay.	No	Yes	Yes
Professional equipment rack with shelves, filler panels, etc. and console audio rack system with table top slant mixer rack and straight under desk front face.	Yes	Yes	Yes
Rack mount LED console rack lighting.	Optional	Yes	Yes
Remote AC Power Controller/Conditioners.	Yes	Yes	Yes
Assistive listening and/or multi-language system.	Optional	Optional	Optional
5.1 decoder unit to decode DVD audio into true discrete 5.1 outputs.	Optional	Optional	Optional
Expansion to 7.1 channel system with side fills or 6.1 system with zenith channel	Optional	Optional	Optional